



| Input voltage | Output voltage | Output current | Output power | Efficiency | Size |
|---------------|----------------|----------------|--------------|------------|-------------|
| 9-36V DC | 24V DC | 10 Amps | 240 Watts | 97.6% | 100*80*39mm |



The WG9-36S2410 is a Non-isolated DC-DC converter that uses a synchronous rectification technology and features high efficiency and power density. It has the dimensions of $100 \, \text{mm} \times 80 \, \text{mm} \times 39 \, \text{mm}$ and provides the rated output voltage of 24V and the maximum output current of $10 \, \text{A}$.

Features

- High efficiency: 97.6% (@ 24 Vin, 25℃)
- Input transient absorption protection
- Remote ON/OFF control (optional)
- Support -40°C environment
- 100% full load burn-in test
- Short circuit, Overload, Over temperature and Over voltage protections
- Waterproof level IP68
- 2 Years warranty

Applications

- Industrial
- Alternative Energy
- Golf Cart & EV Cars
- Forklift
- Electromotor
- Telecommunications
- Boat & Yacht
- Medical and so on.

Model naming method

WG9-36S2410

| WG | : szwengao company name |
|-----|--------------------------------|
| 9-3 | 6 : Input rated voltage |
| S | : Single output type |
| 24 | : Output voltage |
| 10 | : Output current |





Electrical Specifications

Conditions: TA = 25 $^{\circ}$ C (77 $^{\circ}$ F), Airflow = 1 m/s (200LFM), Vin =24V, Vout =24V , unless otherwise specified.

| Parameter | Min. | Typ. | Max. | Units | Remarks |
|-----------------------------|------|-------|-------|---------------------------------------|---|
| Absolute maximum rati | ngs | | | | ' |
| Operating ambient | | | | _ | |
| temperature | -40 | - | +50 | ° C | |
| Shell ambient | | | | | |
| temperature | -40 | - | 80 | ° C | |
| Storage temperature | -55 | - | 100 | ° C | |
| Operating humidity | 5 | - | 95 | % | Non-condensing |
| Atmospheric pressure | 62 | - | 106 | Кра | - |
| Altitude | _ | - | 4000 | m | |
| Cooling way | - | - | - | | Natural cooling |
| Input characteristics | | | | | |
| Input voltage | 9 | 12/24 | 36 | V | Continuous |
| Max. input voltage | - | - | 40 | V | |
| Undervoltage shutdown | 7.1 | 7.7 | 7.9 | V | Automatic recovery |
| Undervoltage recovery | 7.3 | 7.8 | 8.3 | V | Automatic recovery |
| Max. input current | - | - | 34 | A | Vin =7.7V; Iout =10A |
| No load current | - | 110 | 140 | mA | Vin =24V |
| Positive electrode cable | 10 | - | - | AWG | If the wire length is greater than 50cm, it is |
| Negative electrode cable | 10 | _ | _ | AWG | recommended to use a thicker wire diameter. |
| Enable PIN cable | 22 | _ | _ | AWG | If the product has this feature |
| Fuse | - | 30*2 | _ | A | Product input positive has built-in fuse |
| Output characteristics | | 30 2 | | , , , , , , , , , , , , , , , , , , , | Troduce impac positive has balle in rase |
| Efficiency | _ | 97.6 | _ | % | Vin =24V; Iout =10A |
| Output voltage | 23.9 | 24.0 | 24.3 | V | Vin =24V; Iout =10A |
| Regulator accuracy | - | ±1 | - | % | VIII - 21V, 10dt - 10/1 |
| Voltage regulation | - | ±1 | _ | % | |
| Load Regulation | _ | ±1 | _ | % | |
| Overvoltage protection | 38 | 39 | 40 | V | @25° C Automatic recovery |
| Output current | 0 | | 10 | A | @25 C Automatic recovery |
| Overcurrent protection | 12 | 13 | 14 | A | Vin=24V |
| External capacitance | 0 | 2000 | 10000 | Λ μF | VIII-24V |
| Output ripple and noise | - | 140 | 220 | µг mVp-p | Vin =9-36V; Iout=10A Bandwidth: 20 MHz; |
| | | 70 | | | VIII – 9–36V, 10ut–10A Bandwidun. 20 Minz, |
| Output voltage rise time | | | 100 | mS | |
| Boot delay time | - | 100 | 130 | mS 0/ | Vin_24V |
| Out voltage overshoot | - | 1 | 2 | % | Vin=24V |
| Over temperature protection | 100- | 105- | 110 | ° C | Shell temperature, @ 106° C Restore working |
| Short circuit protection | - | - | - | | Long-term (4 hours) short circuit is not damaged, Hiccup mode |
| Positive electrode cable | 14 | _ | _ | AWG | If the wire length is greater than 50cm, it is |
| Negative electrode cable | 14 | _ | _ | AWG | recommended to use a thicker wire diameter. |





| Safety features | | | | | | |
|------------------------|-----------------|------|-----|--------------------------------|--|--|
| Anti-electric Strength | Input to Output | - | V | Leakage current < 2 Em/ 1 min | | |
| | Input to Shell | ≥500 | V | Leakage current ≤ 3.5mA, 1min, | | |
| | Output to Shell | ≥500 | V | no breakdown, no arcing | | |
| Insulation resistance | Input to Output | | МΩ | | | |
| | Input to Shell | ≥50 | | Test voltage = 500V | | |
| | Output to Shell | | | | | |
| Other characteristics | | | | | | |
| Weight | ≤ 550 | | g | | | |
| Package | White box | | | | | |
| MTBF | ≥200,000 | | Н | Vin =24V; Iout =10A | | |
| Switching frequency | 220±10 | | KHz | | | |

Characteristic Curves

Conditions: TA = 25 $^{\circ}$ C (77 $^{\circ}$ F), Vin = 24V, Vout =24 V , unless otherwise specified.

Figure 1, Efficiency




Figure 2, Power dissipation





Figure 3, Input V-I Iout=10A





Typical Waveforms

Conditions: TA = 25° C (77° F), Vin = 24 V, unless otherwise specified.

Figure 4, 25% - 50% load dynamic




Figure 5, 50% - 75% load dynamic




Figure 6, Output voltage established (Iout = 10A)





Figure 7, Output ripple & noise (Iout = 10A)



Feature Description


Remote On/Off (EN) (Optional)

| Logic | Low level | High level | Left open |
|-------------------|------------|-------------|-----------|
| Enable | (0 - 8Vdc) | (8 - 40Vdc) | |
| Positive logic | Off | On | Off |

Input Undervoltage Protection

The converter will shut down after the input voltage drops below the under-voltage protection threshold for shutdown. The converter will start to work again after the input voltage reaches the input under voltage protection threshold for startup. For the Hysteresis, see the Protection characteristics.

Various circuits for driving the EN



Output Overcurrent Protection

The converter equipped with current limiting circuitry can provide protection from an output overload or short circuit condition. If the output current exceeds the output overcurrent protection set point, the converter enters hiccup mode. When the fault condition is removed, the converter will automatically restart.





Overtemperature Protection

A temperature sensor on the converter senses the average temperature of the module. It protects the converter from being damaged at high temperatures. When the temperature exceeds the over temperature protection threshold, the output will shut down. It will allow the converter to turn on again when the temperature of the sensed location falls by the value of Over temperature Protection Hysteresis

Wiring Instructions


The input and output of this product is terminals. The user should ensure that the input and output wires and terminals are connected reliably and pay attention to the wire diameter to meet the requirements of the power supply current. If the cable to be used is long, it needs Considering the voltage drop of the wire, if the voltage drop is too large, the voltage output at the load end may not meet the load demand. In this case, consider using a thicker wire diameter or reducing the length of the wire. Generally, if long wiring is required. Long line should be used on the side where the current is relatively small.

Thermal Consideration

Sufficient airflow should be provided to help ensure reliable operating of the WG9-36S2410.


Therefore, thermal components are mounted on the top surface of the WG9-36S2410 to dissipate heat to the surrounding environment by conduction, convection, and radiation. Proper airflow can be verified by measuring the temperature at the middle of the base plate.











Shenzhen Wengao Electronic Co., Ltd

A: 2/F A, Bldg.A2, Anle Ind. Hangcheng RD., Xixiang Street, Baoan Dist., Shenzhen, China 518102

T: +86 755 29418061 F: +86 755 29418061 E: <u>info@wengaoelec.com</u> W: <u>www.wengaoelec.com</u>